

PHONE RECORDER **SPECIFICATIONS AND FEATURES**

Features REC-ADPT:

- Selector switch for different telephone handset wiring.
- Record level control.
- Does not require batteries or Plug Pack.
- 2.0m shielded lead with 3.5mm Stereo Phono Plug.
- Compact size: L=80mm, W=55mm, H=30mm
- Approvals: Australia (ACMA). Europe (CE)

Features REC-ADPT-LC:

- Record level control.
- Does not require batteries or Plug Pack.
- 2.0m shielded lead with 3.5mm Stereo Phono Plug.
- Compact size: L=80mm, W=55mm, H=30mm
- Approvals: Australia (ACMA). Europe (CE)

Features REC-ADPT-USB:

- Does not require batteries or Plug Pack, powered from USB.
- Does not require sound card
- LED indicator to show, correct selector switch position, USB connection and record status.
- Record level control.
- USB cable included.
- Optional Y connector to allow unit to be mounted away from the Telephone.
- Compact size: L=80mm, W=55mm, H=30mm
- Compatible with Windows ME\2000\XP, Mac and Linux.
- Approvals: Australia (ACMA).

Features: REC-ADPT-A

- Selector switch for different Telephone handset wiring.
- LED to indicate correct selector switch position.
- Pre-Amplifier to boost near end voice.
- Record Level Control.
- 9 Volt DC Plug Pack.
- 2.0m shielded lead with 3.5mm Stereo Phono Plug.
- Compact size: L=80mm, W=55mm, H=30mm
- Optional Y connector to allow unit to be mounted away from the Telephone.
- Approvals: Australia (ACMA).

Features: REC-ADPT-SI

- Selector switch for different telephone handset wiring.
- Record level control.
- Powered by your telephone - does not require batteries or Plug Pack.
- Compact size: L=80mm, W=55mm, H=30mm
- Level control to adjust the output level (your voice) from the Audio Mixing Panel to suit your telephone.
- Approvals: ACMA, AS/NZS 60950 (3000V Isolation).

<http://www.radiosupport.com/>